

BHG - BORE HOLE GRADIOMETER



KEY FEATURES

- 1 LCD Display
- 2 Connectors Panel
- 3 Connectivity Cables
- 4 Control Panel
- 5 Bore Hole Gradiometer
- 6 Audio Speakers

FEATURES

- ▷ Heavy-duty sensor cable acts as lanyard. 30', 50', 100' (non-standard lengths available)
- ▷ High-quality connectors and "Toilet Seat" cover over headset jack. "Seacon" connectors available.
- ▷ Alligator clips for 12-volt auxiliary power.
- ▷ Gel-cell auto-charges when auxiliary power connected.
- ▷ "Zero" to "Null" gradient.
- ▷ Permanent gel-cell battery-mounted under electronics panel.
- ▷ Bull-nosed and tapered sensor on BHG; longer sensor on MUL for diver or boat towing.
- ▷ 1 year warranty

SPECIFICATIONS

CONTROLS

- ▷ On, Off
- ▷ Volume Up and Down
- ▷ Range setting (Gain or Sensitivity) Up and Down
- ▷ Zero, Plus and Minus
- ▷ Auto Zero - Automatic self-adjusting

OUTPUTS

- ▷ Audio Frequency Pitch (speaker and jack for headset)
- ▷ Visual LCD Display
- ▷ Bar Graph - range Gain setting - milligauss
- ▷ RS-232 PC connection (cable included)
- ▷ Control all keypad functions data log range, keypad and signal settings works with hyper terminal or equivalent

POWER OPTIONS

- ▷ Internal Battery: 12-volt, 7.2Ah sealed lead acid
- ▷ Battery Life: 72 hours continuous use, charges to full overnight
- ▷ External Power: 12 to 15-volt, cable included
- ▷ Internal battery charging circuit is enabled when external power or AC charging cable is connected

DIMENSIONS

- ▷ Electronics: 16.9" w x 10" h x 6.5" d
- ▷ Sensor: 1.625" d x 34.375" L (4.13cm x 87.3cm)



Bore Hole Gradiometer

- ▷ Durable detector locates large ferrous metal objects by being lowered into drilled boring holes.
- ▷ Bull-nosed and tapered sensor.

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41

Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес: sca@nt-rt.ru | <http://subsurface.nt-rt.ru>